


4.8-5.3 GHz Multi-Stage Power Amplifier

FEATURES

- 4.8-5.3GHz Operating Frequency Range
- 36.5dBm Output Power at 1dB Compression
- 27.0 dB Typical Power Gain @1dB gain compression
- -45.0Bc Typical OIM3@ each tone Pout 24dBm
- Non-Hermetic Metal Flange Package

APPLICATIONS

- Point-to-point and point-to-multipoint radio
- Military Radar Systems



Caution! ESD sensitive device.

ELECTRICAL CHARACTERISTICS (T_b = 25 °C, 50 ohm, VD1=7V, VD2=10V, V_{gg}=-5V)

SYMBOL	PARAMETER/TEST CONDITIONS	MIN	TYP	MAX	UNITS
F	Operating Frequency Range	4.8		5.3	GHz
P1dB	Output Power at 1dB Gain Compression	35.5	36.5		dBm
G1dB	Gain @1dB gain compression	24	27		dB
OIMD3	Output 3 rd Order Intermodulation Distortion @Δf=10MHz, Each Tone Pout 24dBm		-45		dBc
Input RL	Input Return Loss		-12	-10	dB
Output RL	Output Return Loss		-15	-10	dB
VD1	Drain Supply Voltage 1		7		V
VD2	Drain Supply Voltage 2		10		V
I_{DQ1}	Quiescent Drain Current 1		800		mA
I_{DQ2}	Quiescent Drain Current 2		1600		mA
V_{gg}	Gate Supply Voltage		-5		V
R_{th}	Thermal Resistance		3.5		°C/W
ΔT_{ch}	Channel Temperature Rise			80	°C

Note: Turn on/off sequence is required: ---to turn on: apply -5V on both V_{gg} first, then +7V and +10V.
 ---to turn off: turn +7V and +10V off first, then turn -5V off


4.8-5.3 GHz Multi-Stage Power Amplifier

MAXIMUM RATINGS @Tb=25°C

SYMBOL	CHARACTERISTIC	ABSOLUTE ¹	OPERATING ²
V _{D1}	Drain Supply Voltage 1	11V	8V
V _{D2}	Drain Supply Voltage 2	14V	11V
V _{gg}	Gate Supply Voltage	-8V	-6 V
I _{gg}	Gate Current	150mA	50 mA
P _{IN}	Input Power	20dBm	@ 3dB compression
T _{CH}	Channel Temperature	175°C	165°C
T _{STG}	Storage Temperature	-65/175°C	-65/175°C
P _T	Total Power Dissipation	29.8W	25W

Notes: 1. Operating the device beyond the absolute maximum rating may cause permanent damage.
 2. Operating beyond the operating maximum rating may reduce MTTF of the device.

Package Dimension and Pin Assignment



Dimensions are in inches
 * NC: No connection inside the package



EIM4853-5

4.8-5.3 GHz Multi-Stage Power Amplifier

DISCLAIMER

EXCELICS SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. EXCELICS DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN.

LIFE SUPPORT POLICY

EXCELICS SEMICONDUCTOR PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF EXCELICS SEMICONDUCTOR, INC.

AS HERE IN:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

Specifications are subject to change without notice.

Excelics Semiconductor, Inc. 310 De Guigne Drive, Sunnyvale, CA 94085
Phone: 408-737-1711 Fax: 408-737-1868 Web: www.excelics.com

Page 3 of 3
Revision 01